

Kadex

m-Kadex

Quick Start Guide

1 Setting the Date and Time

Kadex

- 1 Press **Menu**, go to **Options** and select **System Options**.
- 2 Select **Date/Time**, insert the correct value and press **OK** to save the settings.

m-Kadex

The m-Kadex has to be connected to the software to set the date and time. Refer to the m-Kadex user manual for more details.

2 Enrolling Card Users

Kadex

- 1 Press **Menu**, go to **User Manage** and select **Enroll User**. Select **Reg RFID** and press **OK** when you see "New Enroll".
- 2 Key in a **User ID**, and wave the card at the induction area until the card ID is displayed on-screen. Press **OK** to save.

m-Kadex

- 1 Check that the green LED is blinking before proceeding. Then wave the administrator card twice. When the green LED blinks rapidly, wave the new user card at the terminal.
- 2 After the beep, wave the administrator card once to end the enrollment process, or repeat the steps above to enroll more cards.

The Quick Start Guide is intended to provide the user with simple instructions on how to setup the terminal date/time and communication as well as to perform card enrollment and verification. For more details on other topics of terminal management, refer to the terminal's hardware user manual available in the package or online at

- **Kadex:** <http://info.fingertec.com/kadex-4>
- **m-Kadex:** <http://info.fingertec.com/mkadex-4>

© 2015 Timetec Computing Sdn Bhd. All rights reserved • 012015

3 Communication Settings

Kadex

Press **Menu** > **Option** > **COMM opt** > Set value for IP / Subnet mask / Gateway / Dev Num > **OK** to save > **Restart** to apply changes.

Default set value:

IP address - 192.168.1.201


Subnet mask - 255.255.255.0

Gateway - 192.168.1.1


m-Kadex

Connect m-Kadex to the software configure settings. Refer to m-Kadex hardware user manual.

Terminal Overview • Kadex



Terminal Overview • m-Kadex



Software Roadmap

1

ingress
Advanced Access Control System

Installation

The FingerTec Ingress software installer is available in a DVD that comes with all FingerTec terminals. Complete the installation.

2




Online Activation

Use the terminal's serial number to activate your software online. Contact your local reseller or support@fingertec.com if you require offline software activation.

3

Real Time Monitoring In/Out Records
Monitor transactions that occur in the terminals in a real-time manner.

System Overview



All complete hardware and software user guides are available in the FingerTec DVD and downloadable online at <http://user.fingertec.com>