

**FINGERTEC**





Face ID 4

**Quick Start Guide**

# Terminal Overview

ENGLISH



## FACE ENROLLMENT

- 1 Align your eye position to appear in this area.
- 2 Progress bar to indicate progress of face enrollment.
- 3 Status bar to indicate the quality of the captured image; the higher the number, the better the image.



## VERIFICATION MODE

- 1 Adjust your position so your face appears in this area.
- 2 Status bar to indicate the quality of the captured image; the higher the number, the better the image.



## SUCCESSFUL VERIFICATION MODE

The system will display your photo, user ID and name after verifying your identity.

## Quick Start Guide

The Quick Start Guide is intended to provide the user with simple instructions on how to setup the terminal date/time and communication as well as to perform face enrollment and verification. For more details on other topics of terminal management, refer to the terminal's hardware user manual available in the package or online at

• <http://info.fingertec.com/faceid4-4>

## 2 Enrolling Face

*Refer to hardware user manual.*

1. Press **Menu** and select **User**.
2. Enter your **User ID** and select **Face**.
3. Follow the instructions and align your eye position to the green rectangle on the screen to enroll your face.
4. Once the enrollment process is done, select the suitable **Privilege** level, and press **Save**.

## 1 Setting the Date and Time

1. Press **Menu**, select **Date/Time** and set the value.
2. You have two options for time format, 12-hour format or 24-hour format.

## 3 Communication Settings

**To input the IP address:** Press Menu > Connection > Connection > IP Addr > Key in IP address.

**To input Subnet mask:** Press Menu > Connection > Connection > NetMask > Insert the numbers.

**To input Gateway:** Press Menu > Connection > Connection > Gateway > Insert the numbers.

## 4 Activating the Terminal on the TCMS V2 Software



1. Double click the TCMS V2 software icon.
2. Click on **Devices** and double click **Setup FingerTec Terminals**.
3. Click **Add** and enter your TCMS V2 Product Key : Refer to the reverse side of the DVD.
4. Select the terminal under **Model**.
5. Insert the **Device ID** and **IP Address** into the columns.
6. Uncheck the **Disabled** checkbox column.
7. Wait for the software to link to the terminal.
8. Enter your Activation Key and click **OK**.

## 5 Download User and Data from Terminal

1. Click **Devices** and double click **Employee Management**.
2. Click **Download Employee**.
3. At the User ID column, select **All**.
4. At Selected Data please tick on the following check boxes: **Face**, **Card ID**, **Username + Privilege + Password**.
5. Click **Apply** and **Save Employee**.
6. Click **Devices** and double click **Download Data From Terminal**.
7. Click **Apply** to start the download.

## 6 Generating Report

1. Click on the **Report** Icon.
2. Select report type **Employee Time Card**.
3. Select the report's **Date range**.
4. Click **Preview** and **Print**.



# TCMS V2 Roadmap



## 1 Software Initial Setup

The TCMS V2 software installer is available in the FingerTec DVD which comes with all FingerTec terminals.

## 2 FingerTec Terminal Management

Connect your FingerTec terminals to TCMS V2 via online terminal activation using the Product Key printed on the license sticker. Please contact your local reseller or [support@fingertec.com](mailto:support@fingertec.com) if an Internet connection is not available.



Product Key    Serial Number

## 3 System Overview

### User's Management

Add, delete, edit and manage user information and transaction logs.

### Attendance Calculation Setup

Attendance rules and calculation formulas must be figured out to obtain correct attendance reports.

### Download attendance records from terminals

Retrieve the transaction logs stored in the terminals into the server.

### Check and edit attendance records

Review the records edit / insert / check for missing records.

### Generating attendance reports

Generate professional and presentable reports for analysis.

### Export attendance records for payroll or 3rd party software

Integrate the attendance records retrieved from FingerTec terminals to a relevant 3rd party software/payroll.

*All complete hardware and software user guides are available in the FingerTec DVD and downloadable online at <http://user.fingertec.com>*